

8 Way Active Splitter with Aux Input 30MM-DS08

An active 8 way splitter for use in DigiHUB enclosures for the distribution of FTA and in house channels. Features 2 inputs, one for FTA antenna and one for local services to be combined.

Features and Benefits

- » 2 in 8 out DigiHUB splitter amplifier for distribution of TV signal. Product dimensions 160x72x35mm (WxHxD)
- » Built in amplifier with gain control
- » 4G filter built in to prevent interference
- » Can be remote powered from output 4 or locally powered by DC jack
- » Pass power to a Masthead amplifier via the input port (switch activated)
- » Max 85dBuV output per port with power supply (14VDC 300mA) included

